

TABLE 1 FACTORY SET GA800 CONFIGURED DRIVE PARAMETERS

PARAMETER	DATA	UNIT	DESCRIPTION/REMARKS
A1-02	SEE TABLE 2	N/A	CONTROL METHOD SELECTION
b1-01	SEE TABLE 4 OR 5	N/A	FREQUENCY REFERENCE SELECTION 1
b1-02	SEE TABLE 4 OR 5	N/A	RUN COMMAND SELECTION 1
b1-15	SEE TABLE 4 OR 5	N/A	FREQUENCY REFERENCE SELECTION 2
b1-16	SEE TABLE 4 OR 5	N/A	RUN COMMAND SELECTION 2
C6-01	SEE TABLE 3	N/A	DRIVE DUTY RATING
d1-01	10.0	HZ.	FREQUENCY REFERENCE 1 - SEE TABLE 4 OR 5
d1-02	20.0	HZ.	FREQUENCY REFERENCE 2 - SEE TABLE 5
E1-01	208	VOLTS	INPUT VOLTAGE SETTING FOR BASE NUMBER "D____"
	240(480)		STANDARD INPUT VOLTAGE SETTING
	600		INPUT VOLTAGE SETTING FOR BASE NUMBER "C____"
E1-05	208	VOLTS	MAXIMUM OUTPUT VOLTAGE FOR BASE NUMBER "D____"
	230(460)		STANDARD MAXIMUM OUTPUT VOLTAGE SETTING
	575		MAXIMUM OUTPUT VOLTAGE SETTING FOR BASE NUMBER "C____"
E2-01	---	AMPS	MOTOR FULL LOAD AMPS (MUST BE SET BY USER)
H1-05	SEE TABLE 4 OR 5	N/A	MULTI-FUNCTION DIGITAL INPUT TERMINAL S5 FUNCTION SELECTION
H1-06	SEE TABLE 4 OR 5	N/A	MULTI-FUNCTION DIGITAL INPUT TERMINAL S6 FUNCTION SELECTION
H3-02	SEE TABLE 4 OR 5	N/A	TERMINAL A1 FUNCTION SELECTION
H3-06	SEE TABLE 4 OR 5	N/A	TERMINAL A3 FUNCTION SELECTION
H3-09	SEE TABLE 4 OR 5	N/A	TERMINAL A2 SIGNAL LEVEL SELECTION
L3-04	SEE TABLE 2	N/A	STALL PREVENTION DURING DECELERATION SELECTION
o2-03	1	N/A	USER INITIALIZATION FACTORY SET PARAMETER DEFAULT VALUES (FOUND IN A1-03= "1110")
o3-02	1	N/A	COPY ALLOWED SELECTION ENABLED

TABLE 2 G8C FACTORY SET DRIVE PARAMETERS

OPTION PRESENT	PARAMETER	
	A1-02	L3-04
NONE	2 ■	1 ■
PJ OR PL	2 ■	0
TX	3	1 ■
(PJ OR PL) AND TX	3	0

■ = FACTORY 2-WIRE INITIALIZATION DEFAULT SETTING

TABLE 3 G8C FACTORY SET DRIVE PARAMETERS

GA800 CONFIG. MODEL NO. BASE NUMBER G8C()xxxx	PARAMETER
1	1 ■
4	0

■ = FACTORY 2-WIRE INITIALIZATION DEFAULT SETTING

DRIVE OPERATION MODE SELECTION WITHOUT THE HAND/OFF/AUTO SELECTOR SWITCH OPTION TY

TABLE 4 G8C FACTORY SET DRIVE PARAMETERS

OPTION PRESENT	PARAMETER										DRIVE SPEED REFERENCE			DRIVE RUN/STOP CONTROL		
	b1-01	b1-02	b1-15	b1-16	H1-05	H1-06	H3-02	H3-06	H3-09	H3-09	DRIVE KEYPAD	0-10VDC AT TERM. A1 4-20mADC AT TERM. A2, OR 0-10VDC AT TERM. A3	SPEED POT	SERIAL COMM.	DRIVE TERMINAL S1 OR S2	DRIVE KEYPAD
NONE +	1 ■	1 ■	0 ■	0 ■	3 ■	4 ■	0 ■	2 ■	2 ■		YES			YES		
NONE	0	1 ■	0 ■	0 ■	3 ■	4 ■	0 ■	2 ■	2 ■	d1-01				YES		
NONE	1 ■	0	0 ■	0 ■	3 ■	4 ■	0 ■	2 ■	2 ■		YES				YES	
NONE	0	0	0 ■	0 ■	3 ■	4 ■	0 ■	2 ■	2 ■	d1-01					YES	
TZ +	1 ■	1 ■	0 ■	0 ■	3 ■	4 ■	0 ■	2 ■	2 ■			YES		YES		
TZ	1 ■	0	0 ■	0 ■	3 ■	4 ■	0 ■	2 ■	2 ■			YES			YES	
TC,TD,TG,TH OR TQ +	3	3	0 ■	0 ■	3 ■	4 ■	0 ■	2 ■	2 ■				YES			YES
TC,TD,TG,TH OR TQ	1 ■	3	0 ■	0 ■	3 ■	4 ■	0 ■	2 ■	2 ■		YES					YES
TC,TD,TG,TH OR TQ	0	3	0 ■	0 ■	3 ■	4 ■	0 ■	2 ■	2 ■	d1-01						YES
TC,TD,TG,TH OR TQ	3	1 ■	0 ■	0 ■	3 ■	4 ■	0 ■	2 ■	2 ■				YES	YES		
TC,TD,TG,TH OR TQ	3	0	0 ■	0 ■	3 ■	4 ■	0 ■	2 ■	2 ■				YES		YES	
TZ AND (TC,TD,TG,TH OR TQ)	1 ■	3	0 ■	0 ■	3 ■	4 ■	0 ■	2 ■	2 ■			YES				YES

+ = STANDARD GA800 CONFIGURED SET UP
 ■ = FACTORY 2-WIRE INITIALIZATION DEFAULT SETTING

DRIVE OPERATION MODE SELECTION WITH THE HAND/OFF/AUTO SELECTOR SWITCH OPTION TY

TABLE 5 G8C FACTORY SET DRIVE PARAMETERS

OPTION PRESENT	PARAMETER										DRIVE SPEED REFERENCE			DRIVE RUN/STOP CONTROL			
	b1-01	b1-02	b1-15	b1-16	H1-05	H1-06	H3-02	H3-06	H3-09	CONTROL BOARD SWITCH S1-2(A2)	DRIVE KEYPAD	SPEED POT	SIGNAL LEVEL AT TB1 (4) AND (5)	SERIAL COMM.	HAND/OFF/AUTO SWITCH IN THE "HAND" POSITION	RUN CONTACT AT TB1 (1) AND (2)	SERIAL COMM.
TY +	1 ■	1 ■	0 ■	0 ■	3 ■	4 ■	0 ■	F	2 ■	1 ■	d1-02		4 TO 20mADC		YES	YES	
TY	1 ■	1 ■	0 ■	0 ■	3 ■	4 ■	0 ■	F	0	V	d1-02		0 TO 10VDC		YES	YES	
TY AND TZ +	1 ■	1 ■	0 ■	0 ■	3 ■	4 ■	2	F	2 ■	1 ■		YES	4 TO 20mADC		YES	YES	
TY AND TZ	1 ■	1 ■	0 ■	0 ■	3 ■	4 ■	2	F	0	V		YES	0 TO 10VDC		YES	YES	
TY AND (TC,TD,TG,TH OR TQ)	0	1 ■	3	3	2	1	0 ■	F	2 ■	1 ■	d1-01			YES	YES		YES
TY, TZ AND (TC,TD,TG,TH OR TQ)	1 ■	1 ■	3	3	2	1	0 ■	F	2 ■	1 ■		YES		YES	YES		YES

+ = STANDARD GA800 CONFIGURED SET UP
 ■ = FACTORY 2-WIRE INITIALIZATION DEFAULT SETTING

YASKAWA		DRAWN BY: K. MALUSIC	DATE: 8/1/18	TITLE: DRIVE PARAMETERS GA800 CONFIGURED TYPE 1
		CHECKED: N. LAWS	DATE: 8/1/18	
		TECH: K. FLIERL	DATE: 8/1/18	
		APPROVED: K. FLIERL	DATE: 8/1/18	
		ORIGINAL DESIGN: K. MALUSIC	DATE: 8/1/18	
THIS DOCUMENT AND INFORMATION CONTAINED IN IT ARE CONFIDENTIAL, AND CANNOT BE COPIED OR DISCLOSED IN WHOLE OR IN PART WITHOUT THE EXPRESS WRITTEN CONSENT OF YASKAWA AMERICA INC.		SIZE: D	REVISION: 00	PAGE: 1 of 1
		DRAWING#: UDE00579		

REVISIONS				
REV.	DESCRIPTION	ECO #	DRAWN BY	DATE
00	INITIAL RELEASE	-	KM	8/1/18