

The recommended bend radius is 90mm or larger for moving parts of machines, such as robots.

The recommended bend radius is 20mm or larger for fixed installations.

MOTOR END CONNECTOR

	MOTOR END CONTROL					
Item		Description				
Order Number		JZSP-C7M9-3-E				
Manufacturer		J.S.T. Mfg. Co., Ltd.				
User Instructions		JFA Connector J-3700				
Compo- nents	Receptacle	J37S-06FMH-8KL-M-CF				
	Contacts	Power terminals: SJ3F-41GF-P1.8 Holding brake terminals: SJ3F-01GF-P1.8				
Applicable Wire Sizes		Power terminals: AWG16 Holding brake terminals: AWG20 to AWG24				
Applicable Cable Diameter		8 mm ±0.3 mm				
Outer Diameter of Insulating Sheath		Power terminals: 1.53 mm to 2.5 mm Holding brake terminals: 1.11 mm to 1.86 mm				
Mounting Screws		M2.5 pan-head screws				
Crimp- ing Tool*	Hand Tool	Power terminals: YRF-880 Holding brake terminals: YRF-881				
	Applicator	Power terminals: APLMK SJ3F/M41-20 Holding brake terminals: APLMK SJ3F/M01-20				
External Dimensions [mm]		Pin 1 Cable on Load Side (36.6) Motor mounting surface Pin 1 19.3				

RAW CABLE

Item	Flexible Cable	
Order Number*	JZSP-CSM81-□□-E (maximum length: 50 m)	
	UL2517 (rated temperature:105°C) AWG16 × 4C, AWG22 × 2C	
Specifications	Power lines: AWG16 (1.31 mm²) Outer diameter of insulating sheath: 2.35 mm	
	Holding brake lines: AWG22 (0.33 mm²) Outer diameter of insulating sheath: 1.37 mm	
Finished Diameter	8 mm ±0.3 mm	
Internal Structure and Lead Colors	(Green) (Rod (White) (Blue)	

^{*} Replace the boxes ($\square\square$) in the order number with the cable length (05, 10, 15, 20, 30, 40, or 50).

WIRING SPECIFICATIONS

SERVOPAC		
Wire Color	Signal	
Green/yellow	FG	

Phase W

Phase V

Phase U

Blue

White

Red

Signal	Pin
FG	1
Phase W	2
Phase V	3
Phase U	4
_	5
_	6

Servomotor Connector

ITEM NUMBER	L=Length
JZSP-C7M32F-03-E	3000
JZSP-C7M32F-05-E	5000
JZSP-C7M32F-10-E	10000
JZSP-C7M32F-15-E	15000
JZSP-C7M32F-20-E	20000
JZSP-C7M32F-30-E	30000
JZSP-C7M32F-40-E	40000
JZSP-C7M32F-50-E	50000

THIS DOCUMENT AND THE INFORMATION CONTAINED IN IT ARE PUBLIC AND CAN BE DISCLOSED WITHOUT EXPRESS WRITTEN CONSENT OF YASKAWA AMERICA INC. SPECIFICATIONS ARE SUBJECT TO CHANGE WITHOUT NOTICE FOR ONGOING PRODUCT MODIFICATIONS AND IMPROVEMENTS.

YASKAWA

TITLE:SGM7J-08, SGM7A-08 to -10. 750W to 1.0kW Servomotor Power Cable, No Brake, Toward Load, Flexible, Non-Shielded

TEM #:

JZSP-C7M32F-xx-E (xx = See Chart)

SIZE REVISION PAGE
- 0 1 of 1

SCALE: NTS UNITS: mm

mm SHEET: 1/1

DRAWING #:
CAD-JZSP-C7M32F-xx-E

* A Crimping Tool is required. Contact the connector manufacturer for details.

 REV
 DESCRIPTION
 DATE
 DRAWN BY

 0
 Initial Release
 12/20/2018
 E. SONDERMAN