

YASKAWA

FP605

INDUSTRIAL FAN & PUMP DRIVE



Offering world class Yaskawa quality, along with easy installation and high flexibility, the FP605 Industrial Fan and Pump AC Drive delivers a highly efficient and sustainable solution for all your pump and fan motor control needs.



IP20/UL Type 1



IP55/UL Type 12



IP55/UL Type 12
w/Switch



IP55/UL Type 12
Backside Flange

FP605 INDUSTRIAL FAN & PUMP DRIVE



Bluetooth®

Use the DriveWizard Mobile Application to manage FP605 drives with optional Bluetooth keypad connectivity.

High-Contrast Display

Contrast control offers clear and readable full-text descriptions with pump terminology.

Advanced Keypad Navigation

Shortcuts, scrolling and function keys offer faster navigation.

Automatic Backup Function

Saves the drive's current parameter setting automatically. No user interaction required. After an incident, settings can be easily retrieved from the keypad. An additional four parameter backups can be programmed into the drive.

IP55/UL Type 12 Models

Sealed door with accessible buttons provides dust and water resistance. Available as a standalone IP55/UL Type 12 drive or a standalone IP55/UL Type 12 drive with integrated switch.

24 VDC Standby Power Input

Simplify your wiring and keep your communication network operating even during standby or a power outage.



MicroSD Slot

MicroSD storage for data logging of up to ten user customizable drive monitors.

USB Port (behind keypad)

Easily connect your PC or mobile device to program the drive with or without power.

Real-Time Clock

Real-time clock for time and date stamp of fault information.

LED Status Ring

Determine drive status with a quick glance at the LED status ring and know the FP605 is ready and operating.

Finger Safe Terminals

Euro-Style terminal blocks (240 V: up to 20 HP; 480 V: up to 50 HP) allow for fast and finger safe power wiring of bare wire or ferrule connections.

Power Range

- IP20/UL Type 1
 - 240 VAC: 3 to 150 HP
 - 480 VAC: 3 to 600 HP
- IP55/UL Type 12
 - 240 VAC: 3 to 60 HP
 - 480 VAC: 3 to 125 HP

Bluetooth® and the Bluetooth logo are registered trademarks of Bluetooth SIG, Inc. USA.



Learn more about the FP605 by visiting <https://www.yaskawa.com/fp605>

NO POWER? NO PROBLEM!

The FP605 can be programmed without any power supply connected, even while the drive is still in the box. Simply plug into one of your PC's USB ports or any USB On-the-Go device (Android smartphone or tablet), start programming and enjoy the ease of commissioning.



YASKAWA

Yaskawa America, Inc. 1-800-YASKAWA | Email: info@yaskawa.com | yaskawa.com
Document No. FL.FP605.01 | 05/01/2025 | © 2022 Yaskawa America, Inc.